

3500W / 4.4KVA INVERTER GENERATOR

3500W / 4.4kva Inverter Generator

Powerbuilt's pure power series is as smooth as your power at home.
Pure sine wave, safe for your sensitive electronics, ideal for computers, mobile phones, and battery chargers for cordless tools. All that power, packed into 30kg (net weight), compact for single person lift. Need more power? Easily run two units in parallel to double your power output to 6000watts.

As your emergency power back-up, this unit is ideal for running power tools, water pump, charging up devices/lights, most household appliances, fridge, freezer, jug/kettle.

- Heavy-duty open-frame petrol inverter generator
- Eco throttle reduces fuel consumption and noise at low loads
- 7hp, 3500 Watts (4.4kW) Max, 3200 Watts (4kW) Rated
- Low oil sensor prevents engine damage from low oil
- 7L Fuel tank with fuel gauge, run time up to 4 hours
- Noise output level 74dB @ 7M away
- 2x IP44 15amp plugs, 2x USB ports
- Extra heavy-duty frame

PBI4400X



	MODEL	UNITS	PBI4400X
INVERTER	Max Power	Watts	3500
	Rated Power	Watts	3200
	Max Power	kva	4.4
	Rated Power	kva	4
	Amperage	A	14
	Hertz	Hz	50
	Voltage	V	230
	Socket		2 x 230V 15amp IP44
ENGINE	USB Port		1 x 1 amp 1 x 2.1 amp
	Engine	Hp	7.0
	Engine Size	cc	212
	RPM	RMP	3600
	Fuel Type		91 Unleaded
	Fuel Tank	L	7
	Run time	Hours	4
	Start Up		Recoil
SIZE	Decibel Rating	dba	74dB @ 7m
	Weight (net)	kg	30
	Width	mm	502
	Depth	mm	350
	Height	mm	495

IDEAL FOR RUNNING

Power tools, Water pump
Charging up devices/lights
Fridge, Freezer, Jug/kettle
Most household appliances

